

RESPONSE TO A SETPOINT CHANGE IN PID CONTROLLED TIME-DELAY FEEDBACK SYSTEMS

GIANPASQUALE MARTELLI

ABSTRACT. The response to a setpoint change in PID controlled feedback systems plays an important role for the tuning methods. This response may be easily evaluated in linear systems without delay by solving the related ordinary differential equations. These equations are also obtained for system with delay, if the delay exponential term is approximated to a polynomial by one of the Padé expressions. If this simplification is avoided, one must deal with differential difference equations. In this paper their explicit solution, obtained with the method of steps, is presented. Moreover a second order equation is investigated as example and the complete set of the coefficients formulas is given.

1. INTRODUCTION

The closed-loop response of a feedback control system can be considered one of the main behaviour taken into consideration for a proper tuning. A very common and normally desired goal consists of a deadbeat response (see para. 10.2.5 of [1] p. 171) i. e. the wanted value of the controlled variable, after a setpoint change, is achieved as fast as possible and held within a narrow band. This operation mode has been completely studied and successfully applied only to the systems without delay. The Ziegler-Nichols tuning method [2], which is the most known and used one, considers the quarter amplitude decay ratio, obtains the process parameters values from an open-loop test and consequently gives simple relationships between them and the controller ones. An another is the Kappa-Tau method [3], based on a step response experiment, which supplies parameters relationships obtained applying dominant pole design, at constant maximum sensitivity gain, on typical process control models. Moreover there are optimization criteria, minimizing the integrated error during a step response, but calculated after the reduction of the exponential time-delay term to a polynomial form by means of a Padé approximation (see for example [4]). Finally the actual commercial controllers, which can be single in separate hardware box or multiple in distributed control systems (DCS), are provided with adaptive techniques (see para. 52.4 of [1] p. 825). Most of these techniques are based on step response analysis and the controller parameters are adjusted according to some rules in order to have a performance index inside a preset range.

From these preliminary remarks it follows that a strict and simple formula, not yet available, of a setpoint change response can be helpful for an accurate and safe controller tuning of time-delay systems and hence it will be the aim of this paper.

Date: February 22, 2007.

2000 Mathematics Subject Classification. 93B52; 34A05.

Key words and phrases. differential difference equations, PID controllers, time-delay systems.

The transfer functions of the PID controller $T_c(s)$ and process $T_p(s)$, taken into consideration, are given by

$$(1.1) \quad T_c(s) = k + k_i/s + k_d s$$

$$(1.2) \quad T_p(s) = e^{-s} \frac{\sum_{h=0}^{h=m_b-2} e_h s^h}{\sum_{h=0}^{h=m_a-1} a_h s^h}$$

where $m_b \leq m_a$. The differential difference equation related to the closed-loop transfer function is described by

$$(1.3) \quad \sum_{h=1}^{h=m_a} a_h \frac{d^h y(t)}{dt^h} = - \sum_{h=0}^{h=m_b} b_h \frac{d^h y(t-1)}{dt^h} + \sum_{h=0}^{h=m_c} c_h \frac{d^h f(t-1)}{dt^h}$$

subject to an initial condition of the form $y(t) = y_{0,k}(t)$ for each of the q consecutive intervals $-1 + \tau_{k-1} \leq t \leq -1 + \tau_k$ ($\tau_{k-1} < \tau_k$, $\tau_0 = 0$ and $\tau_q = 1$) and where

- $y(t)$ is the controlled variable
- $f(t)$ is the setpoint
- t is the normalized time referred to the time delay
- a_h , b_h and $c_h = b_h$ are constants
- m_a , m_b and $m_c = m_b$ are positive integers

The solution of (1.3) can be evaluated by means of the method of the Laplace transform, as a contour integral or as an infinite exponential series, or by means of the method of steps [5], [6]. The contour integral cannot be expressed in terms of elementary functions and for the exponential series, helpful for the study of the behaviour for higher values of the independent variable, an approximation is needed; therefore both are not suitable for an accurate evaluation of the solution for low values of the time. On the contrary this is not true for the method of steps, since, denoting $y_{n,k}$ as the solution valid for $n-1 + \tau_{k-1} \leq t \leq n-1 + \tau_k$, $y_{1,k}$ can be analytically evaluated solving (1.3), which can be considered as an ordinary differential equation. Any consecutive $y_{n,k}$ can be analogously determined, but tedious calculations will be necessary at each time if a general expression will not be found.

This general solution exists provided that the initial condition $y_{0,k}(t)$ and the forcing term $f_{n,k}(t)$ are each a finite sum of the terms of the complementary solution of (1.3), but with a null time delay, each multiplied by a polynomial of t . The solution $y_{n,k}(t)$ will be of the same form. In detail:

$$(1.4) \quad y_{n,k}(t) = \sum_{p=1}^{p=m_a} e^{r_p t} \sum_{i=0}^{i=v_{k,p}+n} G_{n,k,p,i}^* t^i$$

$$(1.5) \quad f_{n,k}(t) = \sum_{p=1}^{p=m_a} e^{r_p t} \sum_{i=0}^{i=w_{k,p}+n} F_{n,k,p,i}^* t^i$$

where $v_{k,p}$ and $w_{k,p}$ are positive integers with $v_{k,p} \geq w_{k,p}$, $1 \leq k \leq q$ and r_p are the characteristic roots of the corresponding ordinary differential equation without time delay. These roots are assumed all simple and real in this paper, but the adopted procedure can be used also if multiple real or complex roots are present.

It is worthwhile to note that, thanks to the integrating term of the PID controller, one of the characteristic roots r_p is null and therefore steady initial conditions and setpoint step changes, which are usually encountered in the tuning methods, yield solutions compatible with (1.4).

Since the coefficients $G_{u,k,p,i}^*$ are considered, in the method of steps, unknown for $u = n$ and known for $u = n - 1$, the necessary and sufficient conditions for the correctness of (1.4), for a given u , are:

- (1) equal number of each different term depending on the time $e^{r_p t} t^i$ included in both sides of (1.1), modified by the introduction of (1.4)
- (2) the total number of the coefficients $G_{u,k,p,i}^*$ equal to the sum of the number of all above mentioned terms $e^{r_p t} t^i$ and the continuity equations one.

These two conditions are fulfilled and will be checked in the next Section.

2. MAIN RESULTS

The sought expressions of the coefficients are simpler if, for each $y_{n,k}$ and $f_{n,k}$, the origin of the temporal axis t_n is assumed coincident with $n - 1$ ($t = n - 1 + t_n$). Therefore (1.4) and (1.5) can be rewritten, for $n \geq 0$, as

$$(2.1) \quad y_{n,k}(t_n) = \sum_{p=1}^{p=m_a} e^{r_p t_n} \sum_{i=0}^{i=v_{k,p}+n} G_{n,k,p,i} t_n^i$$

$$(2.2) \quad f_{n,k}(t_n) = \sum_{p=1}^{p=m_a} e^{r_p t_n} \sum_{i=0}^{i=w_{k,p}+n} F_{n,k,p,i} t_n^i$$

Since $t_{n-1} - 1 = t_n$ holds and since the transformations from (1.4) to (2.1) and from (1.5) to (2.2) substitute t with t_n in $y_{n,k}$ and with t_{n-1} in $y_{n-1,k}$ and $f_{n-1,k}$, (1.3) becomes

$$(2.3) \quad \sum_{h=1}^{h=m_a} a_h \frac{d^h y_{n,k}(t_n)}{dt_n^h} = - \sum_{h=0}^{h=m_b} b_h \frac{d^h y_{n-1,k}(t_n)}{dt_n^h} + \sum_{h=0}^{h=m_c} c_h \frac{d^h f_{n-1,k}(t_n)}{dt_n^h}$$

subject to the following continuity equations:

$$(2.4) \quad \begin{aligned} y_{n,1}(0) &= y_{n-1,q}(1) \quad \text{for } k = 1 \\ y_{n,k}(\tau_{k-1}) &= y_{n,k-1}(\tau_{k-1}) \quad \text{for } k > 1 \end{aligned}$$

$$(2.5) \quad \begin{aligned} \frac{d^h y_{n,1}(0)}{dt_n^h} &= \frac{d^h y_{n-1,q}(1)}{dt_n^h} \quad \text{for } k = 1 \\ \frac{d^h y_{n,k}(\tau_{k-1})}{dt_n^h} &= \frac{d^h y_{n,k-1}(\tau_{k-1})}{dt_n^h} \quad \text{for } k > 1 \text{ and } 0 < h < m_a \end{aligned}$$

Let introduce in (2.3) the solution (2.1) and its derivatives, evaluated according to (A.1). The necessary and sufficient conditions of the correctness of (2.1) can be detailed for each $n > 0$ and each k as follows:

- (1) number of the terms $e^{r_p t} t^i$
 - (a) left-hand side of (2.3): $\sum_{p=1}^{p=m_a} (v_{k,p} + n)$
it is $0 \leq i \leq v_{k,p} + n$, but the coefficient of $t_n^{v_{k,p}+n}$ is null since it is equal to the characteristic polynomial of the corresponding equation without time delay

- (b) right-hand side of (2.3): $\sum_{p=1}^{p=m_a} (v_{k,p} + n)$
it is $0 \leq i \leq v_{k,p} + n - 1$
- (2) coefficients $G_{n,k,p,i}$ ($1 \leq i \leq v_{k,p} + n$)
 - (a) number of the equations (2.3) (see item (1)): $\sum_{p=1}^{p=m_a} (v_{k,p} + n)$
 - (b) number of the unknowns : $\sum_{p=1}^{p=m_a} (v_{k,p} + n)$
 $G_{n,k,p,0}$ has as coefficient the characteristic polynomial of the corresponding equation without time delay and then disappears
- (3) coefficients $G_{n,k,p,0}$ ($1 \leq p \leq m_a$)
 - (a) number of the equations (2.4) and (2.5): m_a
 - (b) number of the unknowns: m_a

The analytical trasformations required for the evaluation of the coefficients formulas are quite simple. Since series products exist in both sides of (2.3) and the series of the power of t is in the last right position, it is only necessary to shift this series from its actual position to the first left one, modifying accordingly the initial and the final values of all indexes. In this manner the coefficients of $e^{r_p t} t^i$ of both sides, each consisting of the entire expression following this first series, can be correctly equated and therefore (2.3) become an identity for any value of t .

In detail:

- (1) $i > 0$

Introducing (2.1) and its derivatives, evaluated according to (A.1), in the left-hand side *LHS* and in the right-hand side *RHS* of (2.3), we obtain

$$\begin{aligned}
 (2.6) \quad LHS &= \sum_{p=1}^{p=m_a} (S_1(m_a) + S_2(m_a, v_{k,p} + n)) P_{n,k,h,p,i,j} e^{r_p t_n} t_n^j \\
 (2.7) \quad RHS &= + \sum_{p=1}^{p=m_a} \sum_{j=v_{k,p}+n-1}^{j=v_{k,p}+n-1} (Q_{n,k,0,p,j,j} + R_{n,k,0,p,j,j}) e^{r_p t_n} t_n^j \\
 &+ \sum_{p=1}^{p=m_a} (S_1(m_b) + S_2(m_b, v_{k,p} + n - 1)) Q_{n,k,h,p,i,j} e^{r_p t_n} t_n^j \\
 &+ \sum_{p=1}^{p=m_a} (S_1(m_c) + S_2(m_c, w_{k,p} + n - 1)) R_{n,k,h,p,i,j} e^{r_p t_n} t_n^j
 \end{aligned}$$

where

$$\begin{aligned}
 S_1(m) &= \sum_{h=1}^{h=m} \sum_{i=0}^{i=h-1} \sum_{j=0}^{j=i} \\
 S_2(m, z) &= \sum_{h=1}^{h=m} \sum_{i=h}^{i=z} \sum_{j=i-h}^{j=i} \\
 P_{n,k,h,p,i,j} &= a_h r_p^{h-i+j} \frac{i! h!}{j!(i-j)!(h-i+j)} G_{n,k,p,i} \\
 Q_{n,k,h,p,i,j} &= -b_h r_p^{h-i+j} \frac{i! h!}{j!(i-j)!(h-i+j)} G_{n-1,k,p,i} \\
 R_{n,k,h,p,i,j} &= c_h r_p^{h-i+j} \frac{i! h!}{j!(i-j)!(h-i+j)} F_{n-1,k,p,i}
 \end{aligned}$$

It is now necessary to shift the index j series, in $S_1(m)$ and $S_2(m, z)$, from the last right position to the first left one according to the series identities detailed in Appendix B. Before making equal the coefficients of t^j included in LHS (2.6) and in RHS (2.7) it is worthwhile to note that, for $i = j$, $P_{n,k,h,p,i,j}$ is given by

$$P_{n,k,h,p,i,i} = a_h r_p^h G_{n,k,p,i}$$

and that the following holds

$$(2.8) \quad \sum_{h=1}^{h=m_a} P_{n,k,h,p,i,i} = G_{n,k,p,i} \sum_{h=1}^{h=m_a} a_h r_p^h = 0$$

because the coefficient of $G_{n,k,p,i}$, which is the characteristic polynomial of the corresponding ordinary differential equation without time delay, is null. The coefficients of the terms t^j of LHS (2.6) are consequently deleted as follows:

- (a) term with $j = 0$: $G_{n,k,p,0}$, existing only in this case
- (b) each term from $j = 1$ to $j = n + v_{k,p} - 1$: $G_{n,k,p,j}$
- (c) term with $j = n + v_{k,p}$: $G_{n,k,p,n+v_{k,p}}$, only one present

Finally the coefficient matrix of the system, consisting of $v_{k,p} + n$ linear equations obtained making equal the coefficients of the terms t^j belonging to LHS and RHS , is triangular and provided with m_a diagonals starting from the central one. The unknowns $G_{n,k,p,i}$, from $i = n + v_{k,p}$ to $i = 1$, can be evaluated in function of $G_{n-1,k,p,i}$, for each value of n , k and p , recursively or with the analytical solution of the system, obtained by means of a consecutive elimination of the unknowns.

(2) $i = 0$

Defining $H_{e,n,k,h}(t_n)$ as

$$\begin{aligned} H_{e,n,k,0}(t_n) &= \sum_{p=1}^{p=m_a} e^{r_p t_n} \sum_{i=e}^{i=n+v_{k,p}} G_{n,k,p,i} t_n^i \quad \text{for } h = 0 \\ H_{e,n,k,h}(t_n) &= \frac{d^h}{dt^h} \left(\sum_{p=1}^{p=m_a} e^{r_p t_n} \sum_{i=e}^{i=n+v_{k,p}} G_{n,k,p,i} t_n^i \right) \\ &= \sum_{p=1}^{p=m_a} \left(\sum_{i=e}^{i=h-1} \sum_{j=0}^{j=i} + \sum_{i=h}^{i=n+v_{k,p}} \sum_{j=i-h}^{j=i} \right) r_p^{h-i+j} \\ &\quad \frac{i!h!}{j!(i-j)!(h-i+j)} G_{n,k,p,i} e^{r_p t_n} t_n^j \quad \text{for } h > 0 \end{aligned}$$

(2.4) and (2.5) become, for $0 \leq h \leq m_a - 1$,

$$(2.9) \quad \begin{aligned} \sum_{p=1}^{p=m_a} r_p^h G_{n,1,p,0} &= -H_{1,n,1,h}(0) + H_{0,n-1,q,h}(1) \quad \text{for } k = 1 \\ \sum_{p=1}^{p=m_a} e^{r_p \tau_{k-1}} r_p^h G_{n,k,p,0} &= -H_{1,n,k,h}(\tau_{k-1}) + H_{0,n,k-1,h}(\tau_{k-1}) \quad \text{for } k > 1 \end{aligned}$$

For each value of k the coefficient matrix of the system, consisting of the m_a linear equations (2.9), is a Vandermonde matrix, whose terms of each

column, for $k > 1$, are multiplied by a constant. This system can be analytically solved with respect to the m_a unknowns $G_{n,k,p,0}$ by means of the Cramer's method and of the Laplace's expansion, thanks to the known expression of the Vandermonde determinant, as detailed in Appendix C.

3. EXAMPLES

Let consider a first-order plant and hence assume $m_a = 2$, $m_b = 2$, $a_0 = 0$, $a_1 = 1$, $a_2 = t_p$. Two cases, whose the first related to a preset initial condition with $q > 1$ and to a setpoint always null and the second related to a steady initial condition with $q = 1$ and to a setpoint change from 1 to 0, are examined.

3.1. **Example no.1.** Since $q > 1$, $f_{n,k} = 0$ ($n \geq 0$), (2.3) and (2.1) become

$$(3.1) \quad \begin{aligned} \frac{dy_{n,k}(t_n)}{dt_n} + t_p \frac{d^2 y_{n,k}(t_n)}{dt_n^2} &= -b_0 y_{n-1,k}(t_n) \\ &- b_1 \frac{dy_{n-1,k}(t_n)}{dt_n} - b_2 \frac{d^2 y_{n-1,k}(t_n)}{dt_n^2} \end{aligned}$$

$$(3.2) \quad y_{n,k}(t_n) = \sum_{i=0}^{i=v_{k,1}+n} G_{n,k,1,i} t_n^i + e^{-t_n/t_p} \sum_{i=0}^{i=v_{k,2}+n} G_{n,k,2,i} t_n^i$$

The expressions of $G_{n,k,p,i}$ for $n > 0$ are given by

a) $i > 0$

$$G_{n,k,1,i} = -\frac{b_0}{i} G_{n-1,k,1,i-1} \quad \text{for } i = v_{k,1} + n$$

$$\begin{aligned} G_{n,k,1,i} + t_p(i+1)G_{n,k,1,i+1} &= -\frac{b_0}{i} G_{n-1,k,1,i-1} - b_1 G_{n-1,k,1,i} \\ &\quad \text{for } i = v_{k,1} + n - 1 \end{aligned}$$

$$\begin{aligned} G_{n,k,1,i} + t_p(i+1)G_{n,k,1,i+1} &= -\frac{b_0}{i} G_{n-1,k,1,i-1} - b_1 G_{n-1,k,1,i} \\ &\quad - b_2(i+1)G_{n-1,k,1,i+1} \quad \text{for } i \leq v_{k,1} + n - 2 \end{aligned}$$

$$G_{n,k,2,i} = +\frac{b_3}{i} G_{n-1,k,2,i-1} \quad \text{for } i = v_{k,2} + n$$

$$\begin{aligned} G_{n,k,2,i} - t_p(i+1)G_{n,k,2,i+1} &= +\frac{b_3}{i} G_{n-1,k,2,i-1} + b_4 G_{n-1,k,2,i} \\ &\quad \text{for } i = v_{k,2} + n - 1 \end{aligned}$$

$$\begin{aligned} G_{n,k,2,i} - t_p(i+1)G_{n,k,2,i+1} &= +\frac{b_3}{i} G_{n-1,k,2,i-1} + b_4 G_{n-1,k,2,i} \\ &\quad + b_5(i+1)G_{n-1,k,2,i+1} \quad \text{for } i \leq v_{k,2} + n - 2 \end{aligned}$$

where

$$b_3 = b_0 - \frac{b_1}{t_p} + \frac{b_2}{t_p^2}$$

$$b_4 = b_1 - \frac{2b_2}{t_p}$$

$$b_5 = b_2$$

b) $i = 0, k = 1$

$$G_{n,k,1,i} = + y_{n-1,q}(1) + t_p \frac{dy_{n-1,q}(1)}{dt_n} \\ - t_p G_{n,k,1,i+1} - t_p G_{n,k,2,i+1}$$

$$G_{n,k,2,i} = - t_p \frac{dy_{n-1,q}(1)}{dt_n} \\ + t_p G_{n,k,1,i+1} + t_p G_{n,k,2,i+1}$$

where $G_{n,k,1,i+1}$ and $G_{n,k,2,i+1}$ exist respectively only for $n + v_{k,1} \geq 1$ and $n + v_{k,2} \geq 1$.

c) $i = 0, k > 1$

$$G_{n,k,1,i} = + y_{n,k-1}(\tau_{k-1}) + t_p \frac{dy_{n,k-1}(\tau_{k-1})}{dt_n} \\ - \sum_{h=1}^{h=v_{k,1}+n} (\tau_{k-1} + t_p h) \tau_{k-1}^{h-1} G_{n,k,1,h} \\ - e^{-\tau_{k-1}/t_p} \sum_{h=1}^{h=v_{k,2}+n} t_p h \tau_{k-1}^{h-1} G_{n,k,2,h} \\ G_{n,k,2,i} = - t_p e^{+\tau_{k-1}/t_p} \frac{dy_{n,k-1}(\tau_{k-1})}{dt_n} \\ + e^{+\tau_{k-1}/t_p} \sum_{h=1}^{h=v_{k,1}+n} t_p h \tau_{k-1}^{h-1} G_{n,k,1,h} \\ + \sum_{h=1}^{h=v_{k,2}+n} (-\tau_{k-1} + t_p h) \tau_{k-1}^{h-1} G_{n,k,2,h}$$

3.2. Example no.2. Since $q = 1$, $y_{0,1} = 1$, $f_{n,1} = 1$ for $n = 0$ and $f_{n,1} = 0$ for $n > 0$, (2.3) and (2.1) become

$$(3.3) \quad \frac{dy_{1,1}(t_n)}{dt_n} + t_p \frac{d^2 y_{1,1}(t_n)}{dt_n^2} = 0 \\ \frac{dy_{n,1}(t_n)}{dt_n} + t_p \frac{d^2 y_{n,1}(t_n)}{dt_n^2} = -b_0 y_{n-1,1}(t_n) \\ -b_1 \frac{dy_{n-1,1}(t_n)}{dt_n} - b_2 \frac{d^2 y_{n-1,1}(t_n)}{dt_n^2} \quad \text{for } n > 1$$

$$(3.4) \quad y_{1,1}(t_1) = G_{1,1,1,0} \\ y_{n,1}(t_n) = \sum_{i=0}^{i=n-1} G_{n,1,1,i} t_n^i + e^{-t_n/t_p} \sum_{i=0}^{i=n-2} G_{n,1,2,i} t_n^i \quad \text{for } n > 1$$

Comparing (3.1) and (3.2) with (3.3) and (3.4), it follows that $G_{1,1,1,0} = 1$ and the expressions of the coefficients $G_{n,1,p,i}$, detailed in Example no.1 for $i > 0$ and $i = 0, k = 1$, are valid also for $n > 1$ in Example no. 2 assuming $q = 1$, $v_{1,1} = -1$ and $v_{1,2} = -2$.

4. CONCLUSION

The found explicit solution of neutral differential difference equations will allow to refine the existing tuning procedures and to implement new ones for the PID or other controllers, used in linear systems of unlimited order provided with one time delay.

APPENDIX A. DERIVATIVES OF $y = e^{rt}t^i$

The h th derivative of $y = e^{rt}t^i$ is given by

$$(A.1) \quad \begin{aligned} \frac{d^h y}{dt^h} &= e^{rt} \sum_{j=i-h}^{j=i} \frac{i!h!}{j!(i-j)!(h-i+j)!} r^{h-i+j} t^j \quad \text{for } h \leq i \\ \frac{d^h y}{dt^h} &= e^{rt} \sum_{j=0}^{j=i} \frac{i!h!}{j!(i-j)!(h-i+j)!} r^{h-i+j} t^j \quad \text{for } h > i \end{aligned}$$

These formulas can be checked by comparing the derivative of (A.1) to the expression assumed by (A.1) when h is replaced with $h+1$.

APPENDIX B. IDENTITIES OF SERIES PRODUCTS

Let define the series products $S_1(m)$ and $S_2(m, z)$ as

$$(B.1) \quad S_1(m) = \sum_{h=1}^{h=m} \sum_{i=0}^{i=h-1} \sum_{j=0}^{j=i}$$

$$(B.2) \quad S_2(m, z) = \sum_{h=1}^{h=m} \sum_{i=h}^{i=z} \sum_{j=i-h}^{j=i}$$

Shifting in (B.1) and (B.2) the j series from the third to the second position, we obtain

$$(B.3) \quad S_1(m) = \sum_{h=1}^{h=m} \sum_{j=0}^{j=h-1} \sum_{i=j}^{i=h-1}$$

$$(B.4) \quad S_2(m, z) = S_{21} + S_{22} + S_{23} + S_{24} + S_{25} + S_{26}$$

where

$$\begin{aligned} S_{21} &= \sum_{h=1}^{h=\text{int}[z/2]} \sum_{j=0}^{j=h-1} \sum_{i=h+j}^{i=h+j} \\ S_{22} &= \sum_{h=1}^{h=\text{int}[z/2]} \sum_{j=h}^{j=z-h} \sum_{i=j}^{i=h+j} \\ S_{23} &= \sum_{h=1}^{h=\text{int}[z/2]} \sum_{j=z-h+1}^{j=z} \sum_{i=j}^{i=z} \\ S_{24} &= \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{j=0}^{j=z-h-1} \sum_{i=h+j}^{i=h+j} \end{aligned}$$

$$S_{25} = \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{j=z-h}^{j=h} \sum_{i=h}^{i=z}$$

$$S_{26} = \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{j=h+1}^{j=z} \sum_{i=j}^{i=z}$$

Shifting in (B.3) and in (B.4) the j series from the second to the first position, we obtain

$$S_1(m) = \sum_{j=0}^{j=m-1} \sum_{h=j+1}^{h=m} \sum_{i=j}^{i=h-1}$$

$$S_{21} = \sum_{j=0}^{j=\text{int}[z/2]-1} \sum_{h=j+1}^{h=\text{int}[z/2]} \sum_{i=h}^{i=h+j}$$

$$S_{22} = + \sum_{j=1}^{j=\text{int}[z/2]} \sum_{h=1}^{h=j} \sum_{i=j}^{i=h+j} + \sum_{j=\text{int}[z/2]+1}^{j=z-1} \sum_{h=1}^{h=z-j} \sum_{i=j}^{i=h+j}$$

$$S_{23} = \sum_{j=z+1-\text{int}[z/2]}^{j=z} \sum_{h=z-j+1}^{h=\text{int}[z/2]} \sum_{i=j}^{i=z}$$

$$S_{24} = \sum_{j=0}^{j=z-1-m} \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{i=h}^{i=h+j} + \sum_{j=z-m}^{j=z-2-\text{int}[z/2]} \sum_{h=\text{int}[z/2]+1}^{h=z-1-j} \sum_{i=h}^{i=h+j}$$

$$S_{25} = + \sum_{j=z-m}^{j=z-\text{int}[z/2]-1} \sum_{h=z-j}^{h=m} \sum_{i=h}^{i=z} + \sum_{j=z-\text{int}[z/2]}^{j=\text{int}[z/2]} \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{i=h}^{i=z}$$

$$+ \sum_{j=\text{int}[z/2]+1}^{j=m} \sum_{h=j}^{h=m} \sum_{i=h}^{i=z}$$

$$S_{26} = \sum_{j=\text{int}[z/2]+2}^{j=m+1} \sum_{h=\text{int}[z/2]+1}^{h=j-1} \sum_{i=j}^{i=z} + \sum_{j=m+2}^{j=z} \sum_{h=\text{int}[z/2]+1}^{h=m} \sum_{i=j}^{i=z}$$

Each series identity can be easily verified by means of the Terms Grid, detailed as example in Table 1. for (B.1) and (B.3). The symbol x in the grid cell, whose row and column numbers are respectively i and j , means the existence of the term, whose indexes are i and j .

TABLE 1. Terms Grid of (B.1) and (B.3)

		j				
		0	1	2		h-1
i	0	x				
	1	x	x			
	2	x	x	x		
		x	x	x	x	
	h-1	x	x	x	x	x

APPENDIX C. VANDERMONDE EQUATIONS SYSTEM

A Vandermonde equations system of m th order is described by

$$(C.1) \quad \sum_{j=1}^{j=m} d_j r_j^{i-1} x_i = Z_i \quad 1 \leq i \leq m$$

where d_j , r_j and Z_i are constant. The solution, evaluated with the Cramer's metod, is given by

$$(C.2) \quad x_j = \frac{\sum_{i=1}^{i=m} (-1)^{i+j} U_{i,j} Z_i}{V}$$

where V is the determinant of the coefficient matrix M_V and $U_{i,j}$ is the determinant of the submatrix M_U , obtained deleting the i th row and the j th column from this matrix. The determinant V is obviously a Vandermonde one and also $U_{i,j}$ can be expressed as a sum of products of two Vandermonde submatrix determinants, if it is calculated according to the Laplace's expansion, i. e. assuming

- for the first submatrix M_1
as rows the $i-1$ rows from 1 to $i-1$ of M_V and as columns the $i-1$ columns, belonging to one of the $N = (m-1)!/((i-1)!(m-i)!)$ sets and selected among the $m-1$ ones of M_U .
- for the second submatrix M_2
as rows the $m-i$ rows from $i+1$ to m of M_V and as columns the remaining ones of M_U i.e. not included in M_1 .

In detail:

$$(C.3) \quad V = \prod_{a>b} (r_a - r_b) \prod_{j=1}^{j=m} d_j$$

$$(C.4) \quad U_{i,j} = \sum_{n=1}^{n=N} (-1)^{s_k} W_{i,j,n}$$

where

$$s_n = \sum_{h=1}^{h=i-1} h + \sum_{k=1}^{k=i-1} pa(n, k)$$

$$W_{i,j,n} = \prod_{pa(n,k)>pb(n,k)} (r_{pa(n,k)} - r_{pb(n,k)}) \prod_{k=1}^{k=i-1} d_{pa(n,k)}$$

$$\prod_{qa(n,k)>qb(n,k)} (r_{qa(n,k)} - r_{qb(n,k)}) \prod_{k=1}^{k=m-i} d_{qa(n,k)} r_{qa(n,k)}^i$$

- h is the row number of M_V
- k is the current column number of M_1 or M_2
- $pa(n, k)$ or $pb(n, k)$ is the number of the column, included as k th in M_1 in increasing order, of M_U
- $qa(n, k)$ or $qb(n, k)$ is the number of the column, included as k th in M_2 in increasing order, of M_U

REFERENCES

- [1] W. S. Levine, Ed., *The Control Handbook*. New York: IEEE Press., 1996.
- [2] J. G. Ziegler and N. B. Nichols, "Optimum settings for automatic controllers," *Trans ASME*, vol. 64, pp. 759–768, 1942.
- [3] K. J. Astrom and T. Hagglund, "PID Control - Theory, Design and Tuning," Instrument Society of America, Research Triangle Park, NC, 2nd ed., 1995.
- [4] A. M. Zhuang and D. P. Atherton, "Automatic tuning of optimum PID controllers," *IEE Proceeding - D*, vol. 140, no. 3, pp. 216–224, 1993.
- [5] J. K. Hale and Sjoerd M. Verduyn Lunel, *Introduction to functional differential equations*, Applied Mathematical Sciences, vol. 99, Springer-Verlag New York, 1993.
- [6] R. Bellman and K. Cooke, *Differential Difference Equations*, Academic Press, 1963.

VIA DOMENICO DA VESPOLATE 8 28079 VESPOLATE ITALY
E-mail address: `gianpasqualemartelli@libero.it`